

# RoHS Compliant Circuit Protection Components SM8S20CAG Surface Mount TVS SMD Diode

# **Basic Information**

- Place of Origin:
- Brand Name:
- Certification: UL,REACH,RoHS,ISO

SOCAY

- Model Number:
- Minimum Order Quantity: 50
- Price: Neg
- Delivery Time:



Shenzhen, Guangdong, China

Negotiable 5-8 work days

SOCAY®

## **Product Specification**

Highlight:	RoHS Circuit Protection Compo
<ul> <li>Storage Temperature:</li> </ul>	-55°C To +175°C
• lpp:	204A
<ul> <li>Vc@lpp:</li> </ul>	32.4V
• It:	5mA
• Vbr@lt (Max.):	24.5V
Vbr@lt (Min.):	22.2V
• Ir@Vr @175 :	150µA
• Ir@Vr @25 :	5μΑ
• Vr:	20V
<ul> <li>Package Size:</li> </ul>	DO-218AB
<ul> <li>Product Name:</li> </ul>	TVS Diodes

RoHS Circuit Protection Components, SMD Circuit Protection Components, Surface Mount TVS SMD Diode



# More Images



## **Product Description**

RoHS Compliant Circuit Protection Components SM8S20CAG Surface Mount TVS SMD Diode

### DATASHEET: SM8SXXG Series\_v2309.1.pdf

### Description:

The SM8S series is designed specifically to protect sensitive electronic equipment from voltage transients induced by lightning and other transient voltage events.

		Workin g Peak Revers e Voltage V <sub>RWM</sub> (V)	Breakdown Voltage V <sub>BR</sub> (V)		Test Curren t I <sub>T</sub> (mA)	Maximu m Reverse Leakage I <sub>R</sub> @ V <sub>RWM</sub> (μΑ)	V <sub>RWM</sub> T <sub>J</sub> =175	Maximu	Clampin g Voltage
Uni	Bi		Min.	Max.					
SM8S20 AG	SM8S20C AG	20.0	22.2	24.5	5.0	10	150	204	32.4

Notes:

. Surge current waveform is defined at 10/1000µS waveform

 For all types maximum V<sub>F</sub> = 1.8 V at I<sub>F</sub> = 100 A measured on 8.3 ms single half sine-wave or equivalent square wave, duty cycle = 4 pulses pe minute maximum.

#### Features:

- Product electrical parameters:
- 1. Power: 6600W
- 2. Working voltage: 10.0-43.0V
- 3. Current: 388-95.1A
- 4. Provide one-way/two-way polarity
- 5. Low forward voltage drop and low leakage current
- 6. High surge capability
- 7. Junction passivation optimization design passivation anisotropic rectification technology
- 8. TJ = 175, suitable for high reliability and automotive requirements
- 9. Comply with ISO7637-2 surge specifications (test conditions change)
- 10. Comply with MSL level 1, according to J-STD-020, the maximum LF peak value is 245
- 11. Comply with AEC-Q101 requirements

#### Application:

Automotive Protection.

#### Typical applications of SM8S series automotive grade TVS diodes:

1. Adding TVS diodes to signal and power lines can prevent microprocessors or microcontrollers from malfunctioning due to instantaneous surges, such as electrostatic discharge effects, AC power surges and switching power supply noise.

2. The electrostatic discharge effect can release pulses of more than 10,000V and 60A, and can last for 10ms; while ordinary TTL devices will be damaged when encountering 10V pulses of more than 30ms. TVS diodes can effectively absorb pulses that can cause device damage and eliminate interference caused by switching between buses.

3. Placing the TVS tube between the signal line and the ground can prevent the data and control bus from being affected by unnecessary noise.

Гаскаўніў								
Part Number	Component Package	Quantity	Packaging Option					
SM8SXXG Series	DO-218AB	500 PCS	13" diameter plastic tape and reel, anode towards the sprocket hole					





**SOCAY's main products** include a full range of Ceramic Gas Discharge Tubes (GDT), Transient Suppression Diodes (TVS Diodes), ESD Suppressor, Thyristor Surge Suppressors (TSS), Spark Gap Protectors (SPG), Varistors (MOV), Chip Varistors (MLV), PTC Resettable Fuse, Negative Temperature Coefficient thermistors (NTC Thermistors), Chip Bead, Schottky Diodes, Zener Diode, etc. From circuit design to product testing (and provide test reports), we will provide you with one-stop services in the field of circuit protection. With excellent quality and service, SOCAY has won extensive praise from customers and respect from the industry.

Socay<sup>®</sup> Shenzhen Socay Electronics Co., Ltd. **(**+8618126201429 sylvia@socay.com e socaydiode.com 4/F, Block C, HeHengXing Science & Technology Park, 19 MinQing Road, LongHua District, Shenzhen City, GuangDong Province, China